

IN THE CLAIMS

1. (Currently Amended) A pulse modulation power converter comprising:
a forward path including a forward block-(15, 30), a switching stage (11) for amplifying an output from the forward block, and an output filter (12) for low pass filtering an output signal from the switching stage,
a global feedback path-(13), connected to the low pass filtered output signal, comprising a global feedback block (18, 19) for generating a feedback signal,
means (14) for subtracting said feedback signal from an input signal, and feeding the result to said forward path,
~~e-h-a-r-a-c-t-e-r-i-z-e-d-i-n-t-h-a-t~~ wherein said global feedback block (18, 19) and/or forward block (15, 20)-includes:
means for compensating at least a portion of a phase lag of said output filter,
and
means for obtaining a 180 degrees phase lag at a switching frequency,
thereby achieving conditions for a controlled oscillation at said switching frequency.
2. (Original) A converter according to claim 1, wherein said compensation means include at least N-1 zeroes placed near the output filter cut-off frequency, where N is equal to the order of the output filter.
3. (Original) A converter according to claim 2, wherein said compensation means include at least one zero placed at a higher frequency than the output filter cut-off frequency.
4. (Currently Amended) A converter according to claim 1—3, wherein said means for obtaining a 180 degrees phase lag at the switching frequency comprises at least one high frequency pole.

5. (Currently Amended) A converter according to claim 1—4, wherein said means for obtaining a 180 degrees phase lag at the switching frequency comprises at least one time delay.

6. (Currently Amended) A converter according to ~~one of the preceding claims~~ claim 1, further comprising at least one local feedback path (30) from the output of the switching power stage to at least one summation point in the forward path, said local feedback path (30) comprising a local feedback block (31).

7. (Currently Amended) A converter according to claim 6, wherein said compensation means include at least one pole near the output filter cut-off frequency placed in the local feedback block (31).

8. (Currently Amended) A converter according to ~~any of the preceding claims~~ claim 1, further comprising at least one additional global feedback path (52, 55), connected to the output signal of the output filter (12) and to a summing point (53, 56) preceding the forward block (15).

9. (Currently Amended) A converter according to ~~any of the preceding claims~~ claim 1 implemented in a power conversion system such as AC-DC, DC-AC, DC-DC or any combination of the above mentioned, especially DC-AC converters for audio use and transmission line drivers.